



Productivity Through Protection™

High Speed Fuses

Bussmann® fuses for Danfoss Drives



VLT® 4000 Series

	Model	HP	KW	Standard	Alternate	
				E4273 RK1/JDDZ	E4273 J/JDDZ	E4273 T/JDDZ
200-240 V	4006	5.0	4.0	KTN-R-25	JKS-25	JJN-25
	4008	7.5	5.5	KTN-R-30	JKS-30	JJN-30
	4011	10	7.5	KTN-R-50	JKS-50	JJN-50
	4016	15	11	KTN-R-60	JKS-60	JJN-60
	4022	20	15	KTN-R-80	JKS-80	JJN-80
	4027	25	18.5	KTN-R-125	JKS-125	JJN-125
	4032	30	22	KTN-R-125	JKS-125	JJN-125
	4042	40	30	KTN-R-150	-	-
	4052	50	37	KTN-R-200	-	-
	4062	60	45	KTN-R-250	-	-

KTS fuses from Bussmann may be substituted for KTN for 240 V drives; JJS fuses from Bussmann may be substituted for JJN for 240 V drives.



Productivity Through Protection™

High Speed Fuses

Bussmann® fuses for Danfoss Drives



VLT® 4000 Series

	Model	HP	KW	Standard		Alternate			
				E4273 RK1/JDDZ	E56412/E91958 JFHR2	E4273 J/JDDZ	E4273 T/JDDZ	E4273 H/JDDZ	E125085 JFHR2
380-460 V	4006	5.0	4.0	KTS-R-15	-	JKS-15	JJS-15	-	-
	4008	7.5	5.5	KTS-R-20	-	JKS-20	JJS-20	-	-
	4011	10	7.5	KTS-R-25	-	JKS-25	JJS-25	-	-
	4016	15	11	KTS-R-30	-	JKS-30	JJS-30	-	-
	4022	20	15	KTS-R-40	-	JKS-40	JJS-40	-	-
	4027	25	18.5	KTS-R-50	-	JKS-50	JJS-50	-	-
	4032	30	22	KTS-R-60	-	JKS-60	JJS-60	-	-
	4042	40	30	KTS-R-80	-	JKS-80	JJS-80	-	-
	4052	50	37	KTS-R-100	-	JKS-100	JJS-100	-	-
	4062	60	45	KTS-R-125	-	JKS-125	JJS-125	-	-
	4072	75	55	KTS-R-150	-	JKS-150	JJS-150	-	-
	4075	75	55	-	FWH-150B	-	-	-	-
	4100	100	75	-	FWH-200B	-	-	-	-
	4102	100	75	-	FWH-200B	-	-	-	-
	4122	125	90	-	FWH-250A	-	-	-	-
	4125	125	90	-	FWH-250A	-	-	-	-
	4150	150	110	-	FWH-300A	-	-	-	-
	4152	150	110	-	FWH-300A	-	JJS-300	NOS-300	170M3017
	4200	200	132	-	FWH-350A	-	-	-	-
	4202	200	132	-	FWH-350A	-	JJS-350	NOS-350	170M3018
	4250	250	160	-	FWH-400A	-	-	-	-
	4252	250	160	-	FWH-400A	-	JJS-400	NOS-400	170M4012
	4300	300	200	-	FWH-500A	-	-	-	-
	4302	300	200	-	FWH-500A	-	JJS-500	NOS-500	170M4014
	4350	350	250	-	FWH-600A	-	-	-	-
	4352	350	250	-	FWH-600A	-	JJS-600	NOS-600	170M4016
	4450	450	315	-	FWH-700A	-	-	-	-
	4500	500	355	-	FWH-800A	-	-	-	-
4600	600	400	-	FWH-800A	-	-	-	-	

FWP fuses from Bussmann may be substituted for FWH for 500V drives.

170M fuses from Bussmann shown use -/80 visual indicator. -TN/80 Type T, -/110 or TN/110 Type T indicator fuses of the same size and amperage may be substituted.



Productivity Through Protection™

High Speed Fuses

Bussmann® fuses for Danfoss Drives



VLT® 4000 Series

	Model	HP	KW	Standard			Alternate	
				E4273 RK1/JDDZ	E56412 JFHR2	E125085 JFHR2	E4273 J/JDDZ	E4273 T/ JDDZ
525-600 V	4006	5.0	4.0	KTS-R-8	-	-	JKS-8	JJS-10
	4008	7.5	5.5	KTS-R-10	-	-	JKS-10	JJS-10
	4011	10	7.5	KTS-R-15	-	-	JKS-15	JJS-15
	4016	15	11	KTS-R-20	-	-	JKS-20	JJS-20
	4022	20	15	KTS-R-30	-	-	JKS-30	JJS-30
	4027	25	18.5	KTS-R-35	-	-	JKS-35	JJS-35
	4032	30	22	KTS-R-45	-	-	JKS-45	JJS-45
	4042	40	30	KTS-R-60	-	-	JKS-60	JJS-60
	4052	50	37	KTS-R-75	-	-	JKS-80	JJS-80
	4062	60	45	KTS-R-90	-	-	JKS-90	JJS-90
	4072	75	55	KTS-R-100	-	-	JKS-100	JJS-100
	4100	100	75	-	FWP-125A	-	-	-
	4125	125	90	-	FWP-175A	-	-	-
	4150	150	110	-	FWP-200A	-	-	-
	4200	200	132	-	FWP-250A	-	-	-
	4250	250	160	-	FWP-350A	-	-	-
	4300	300	200	-	FWP-400A	-	-	-
525-600 V (UL)	4102	100	75	-	-	170M3015	-	-
	4122	125	90	-	-	170M3016	-	-
	4152	150	110	-	-	170M3017	-	-
	4202	200	132	-	-	170M3018	-	-
	4252	250	160	-	-	170M4011	-	-
	4302	300	200	-	-	170M4012	-	-
	4352	350	250	-	-	170M4014	-	-
	4402	400	300	-	-	170M5011	-	-

170M fuses from Bussmann shown use -/80 visual indicator. -TN/80 Type T, -/110 or TN/110 Type T indicator fuses of the same size and amperage may be substituted.

170M fuses from Bussmann when provided in the 525-600 V (UL) drives are 170M3015 for VLT 4102, 170M3018 for VLT 4122-4202, and 170M5011 for VLT 4252-4402.